# Southern Illinois University Carbondale **OpenSIUC**

**Articles and Preprints** 

Department of Mathematics

7-2010

## Feedback Linearizable Feedforward Systems: A Special Class

Issa Amadou Tall
Southern Illinois University Carbondale, itall@math.siu.edu

Follow this and additional works at: http://opensiuc.lib.siu.edu/math\_articles
Published in Tall, I. A. (2010). Feedback linearizable feedforward systems: A special slass. *IEEE Transactions on Automatic Control, 55*(7), 1736-1742. doi: 10.1109/TAC.2010.2048051. ©2010

IEEE. Personal use of this material is permitted. However, permission to reprint/republish this material for advertising or promotional purposes or for creating new collective works for resale or redistribution to servers or lists, or to reuse any copyrighted component of this work in other works must be obtained from the IEEE.

## Recommended Citation

Tall, Issa Amadou, "Feedback Linearizable Feedforward Systems: A Special Class" (2010). *Articles and Preprints*. Paper 108. http://opensiuc.lib.siu.edu/math\_articles/108

This Article is brought to you for free and open access by the Department of Mathematics at OpenSIUC. It has been accepted for inclusion in Articles and Preprints by an authorized administrator of OpenSIUC. For more information, please contact opensiuc@lib.siu.edu.

- [11] H. G. Potrykus, F. Allgöwer, and S. J. Qin, "The character of an idempotent-analytic nonlinear small gain theorem," in *Positive Systems* (*Rome*, 2003), ser. Lecture Notes in Control and Inform. Sci. Berlin, Germany: Springer, 2003, vol. 294, pp. 361–368.
- [12] A. R. Teel, "Input-to-state stability and the nonlinear small gain theorem," Private Communication, 2005.
- [13] E. D. Sontag and Y. Wang, "New characterizations of input-to-state stability," *IEEE Trans. Autom. Control*, vol. 41, no. 9, pp. 1283–1294, Sep. 1996.
- [14] K. Gao and Y. Lin, "On equivalent notions of input-to-state stability for nonlinear discrete time systems," in *Proc. IASTED Int. Conf. Control Applications*, 2000, pp. 81–87.
- [15] Z.-P. Jiang and Y. Wang, "Input-to-state stability for discrete-time non-linear systems," *Automatica J. IFAC*, vol. 37, no. 6, pp. 857–869, 2001.
- [16] B. S. Rüffer, "Monotone inequalities, dynamical systems, and paths in the positive orthant of Euclidean n-space," *Positivity*, 2010 Apr. 2009 [Online]. Available: sigpromu.org/reports/Field65\_368.pdf
- [17] I. Karafyllis and Z.-P. Jiang, "A vector small-gain theorem for general nonlinear control systems," in *Proc. Joint 48th IEEE Conf. Decision Control & 28th Chinese Control Conf.*, Shanghai, China, Dec. 2009, pp. 7996–8001.
- [18] I. Karafyllis and Z.-P. Jiang, "A vector small-gain theorem for general nonlinear control systems," *IEEE Trans. Autom. Control*, to be published.
- [19] Z.-P. Jiang and Y. Wang, "A generalization of the nonlinear small-gain theorem for large-scale complex systems," in *Proc. 7th World Congress Intell. Control Autom.*, Jun. 2008, pp. 1188–1193.

## Feedback Linearizable Feedforward Systems: A Special Class

Issa Amadou Tall, Member, IEEE

Abstract—The problem of feedback linearizability of systems in feedforward form is addressed and an algorithm providing explicit coordinates change and feedback given. At each step, the algorithm replaces the involutive conditions of feedback linearization by some, easily checkable. We also reconsider type II subclass of linearizable strict feedforward systems introduced by Krstic and we show that it constitutes the only linearizable among the class of quasilinear strict feedforward systems. Our results allow an easy computation of the linearizing coordinates and thus provide a stabilizing feedback controller for the original system among others. We illustrate by few examples including the VTOL.

*Index Terms*— Feedback linearization, linear ordinary differential equations (ODEs), linear systems, (strict) feedforward forms.

## I. INTRODUCTION

Linear systems constitute, without doubt, the most well-known class of control systems. Their importance resides in the fact that several physical systems can be modeled using linear dynamics making thus their analysis and design very simple. The controllability, observability, reachability, and realization of linear systems have been expressed in very simple algebraic terms. Another crucial property of linear controllable systems is that they can be stabilized by linear feedback controllers. Although not all systems can be modeled using linear dynamics, the approximation of nonlinear phenomena by linear models has proved to be a satisfactory tool for their local study. The drawback of linearization is that some important properties of a nonlinear system, like global controllability, might be lost by the operation. It is not however surprising that the question of transforming nonlinear control systems into linear ones has attracted much attention in the past thirty years. To give a brief account of that, consider a control system

$$\Sigma : \dot{x} = f(x) + g(x)u, (x, u) \in \Re^n \times \Re^m.$$

The two problems below were investigated in the early 80's.

Problem 1: When does there exist, locally or globally, a diffeomorphism  $w = \varphi(x)$  giving rise to new coordinates system  $w = (w_1, \ldots, w_n)^\top$  in which  $\Sigma$  takes the linear form

$$\Lambda : \dot{w} = Aw + bu, \quad w \in \Re^n, \ u \in \Re^m.$$

Problem 2: Can we find a change of coordinates  $w=\varphi(x)$  coupled with an invertible feedback  $u=\alpha(x)+\beta(x)v$  that transform  $\Sigma$  into a linear system  $\Lambda:\dot{w}=Aw+bv$ ?

The first problem was pioneered by Krener [8] and completely solved by the author. The second problem was proposed and partially solved by Brockett [3] in the single-input case (m=1) with constant function  $\beta$ . The general case of *Problem 2* has been solved independently by Hunt and Su [5], and Jakubczyk and Respondek [7] who gave necessary and sufficient geometric conditions in terms of Lie brackets of vector fields defining the system (see Theorem II.1 below). Although those conditions did provide a way of testing the state and feedback linearizability of a system, they

Manuscript received October 16, 2008; revised October 16, 2008, March 30, 2009, May 29, 2009, and December 28, 2009. First published April 12, 2010; current version published July 08, 2010. Recommended by Associate Editor J. J. Winkin.

The author is with Department of Mathematics, Southern Illinois University Carbondale, Carbondale IL, 62901 USA (e-mail: itall@math.siu.edu).

Digital Object Identifier 10.1109/TAC.2010.2048051

offer little on how to find linearizing change of coordinates (and feedback) except by solving a system of partial differential equations (PDEs). If *Problem 2* is solvable with a controllable pair (A, b), then the equilibrium of  $\Sigma$  can be stabilized by the feedback law  $u=-\beta(x)^{-1}(\alpha(x)+\sum_{j=1}^nk_j\varphi_j(x)),$  where the polynomial  $p(\lambda)=\lambda^n+\sum_{j=1}^nk_j\lambda^{j-1}$  is Hurwitz. Hereafter, (A,b) is assumed to be always controllable, i.e., dim span $\{b, Ab, \dots, A^{n-1}b\} = n$ . Feedback linearization techniques have been used to improve the dynamical behavior of chaotic systems (see Lorenz system in [11], [14]) and have been applied to optimal control problems with a recent regain of interest. In [4], the authors used pseudospectral method to solve optimal control subject to feedback linearizable dynamics. Mayer's problem has been considered in [1] (see also [14]) and an optimal solution for globally feedback linearizable time-invariant systems obtained. Recall that Mayer's problem consists of finding u(t) and x(t) with  $t \in [t_0, t_f]$  that minimize a functional cost  $J = \Phi(x(t_f), t_f)$  subject to  $\dot{x} = f(x) + g(x)u$  and inequality constraints  $\tilde{s}(x,u) \leq 0$ ,  $\tilde{c}(x) \leq 0$  with initial and terminal states satisfying  $\Psi(x(t_0),x(t_f))=0$ . Though these papers deal with feedback linearizable systems, dynamics are usually assumed linear, and linearizing coordinates left to be found. In [9], [10] Krstic studied Type I and Type II subclasses of strict feedforward systems and showed they are linearizable by giving explicit coordinates changes. A single-input control system  $\Sigma$  is in feedforward form (FF)-form if

$$\Sigma_{\text{FF}} : \dot{x} = f(x) + g(x)u$$

$$\triangleq \begin{cases} f_j(x) = f_j(x_j, \dots, x_n), \ 1 \le j < n \\ g_j(x) = g_j(x_j, \dots, x_n), \ 1 \le j < n \end{cases}$$

and  $\Sigma$  is in *strict feedforward form* (SFF)-form  $\Sigma_{\rm SFF}$  if

$$\dot{x} = f(x) + g(x)u 
\triangleq \begin{cases}
f_j(x) = f_j(x_{j+1}, \dots, x_n), & 1 \le j \le n \\
g_j(x) = g_j(x_{j+1}, \dots, x_n), & 1 \le j \le n \\
f_n(x) = 0, g_n \in \Re^* = \Re \setminus \{0\}.
\end{cases}$$

For those classes, Krstic mentioned the difficulty, in general, of systematically finding linearizing coordinates. Inspired by his work, we extended the two classes to all state (resp. feedback) linearizable (SFF)systems and provided a state [20] (resp. feedback [21]) linearizing coordinates. Let us first mention that (SFF)-systems have been introduced as early as in the papers of Teel [22], [23] and have been followed since by a growing literature [2], [9], [10], [13], [16], [20]. What made (SFF)-systems appealing is that a stabilizing feedback controller can always be constructed when their linear approximation around the equilibrium is controllable [22], [23]. *Problem 1* were tackled in [17] for the feedforward case. If there is a component  $f_i$  or  $g_i$  that is nonlinear with respect to the variable  $x_i$ , then finding an explicit linearizing coordinates becomes extremely difficult and might necessitate solving PDEs. For that reason we restricted our study to a special class of (FF)-systems, called *feedforward-nice*, for which the components  $f_i$  and  $g_i$  are affine with respect to the variable  $x_j$  for all  $1 \le j \le n$ . In Section II we give our first result as an algorithm allowing to construct explicitly feedback linearizing coordinates in a finite number of steps. We show, at each step, that the involutivity conditions of Theorem II.1 reduce to  $\partial^2 f/\partial x_i^2$  being proportional to  $\partial f/\partial x_i$ ,  $j=n,\ldots,3$ . A change of coordinates, followed by feedback, is thus constructed (bottom up) to cancel all terms containing the variable  $x_i$  except for the corresponding component  $f_{i-1}$  that is normalized. In Section III we consider Type II systems and give necessary and sufficient conditions for their linearization. We illustrate by few examples including the vertical take-off and landing aircraft. Let mention that for general control systems different algorithms have been obtained in [12] and recently in [18], [19]. While

the former uses the integration of a system of 1-forms the latter papers are based on an explicit solving of the flow box theorem and they all differ with the method for feedforward systems.

#### II. MAIN RESULTS

For reasons mentioned previously, we deal with a subclass of (FF)-systems for which the components  $f_j(x_j,\ldots,x_n)$  and  $g_j(x_j,\ldots,x_n)$  are affine with respect to  $x_j$  for  $1 \leq j \leq n$ . This subclass,  $\Sigma_{\mathrm{FFnice}}$ :  $\dot{x} = f(x) + g(x)u$ , call it *feedforward-nice* is hereby described in the x-coordinates by

$$\begin{cases} f_j(x) = x_j \tilde{f}_j(x_{j+1}, \dots, n) + \hat{f}_j(x_{j+1}, \dots, x_n), \ 1 \le j \le n \\ g_j(x) = x_j \tilde{g}_j(x_{j+1}, \dots, x_n) + \hat{g}_j(x_{j+1}, \dots, x_n), \ 1 \le j \le n \end{cases}$$

with  $\hat{f}_j(0) = 0$ ,  $f_n = 0$ , and  $g_n \in \Re^*$ . We suppose that  $\Sigma_{\text{FFnice}}$  is linearly controllable and, in particular,  $(\partial \hat{f}_j / \partial x_{j+1})(0) \neq 0$  for  $1 \leq j \leq n-1$ . We recall briefly the main result of [17].

### A. State Linearization

Consider  $\Sigma_{\rm FF\, ni\, ce}$  and apply successively changes of coordinates  $z=\phi(x)$ 

$$\begin{cases} z_{j} = x_{j}, \ j \neq k, \\ z_{k} = x_{k} \tilde{\phi}_{k}(x_{k+1}, \dots, x_{n}) + \hat{\phi}_{k}(x_{k+1}, \dots, x_{n}) \end{cases}$$
(II.I)

with

$$\tilde{\phi}_k = \exp\left(-\int_0^{x_n} \tilde{g}_k(x_{k+1}, \dots, x_{n-1}, \varepsilon), d\varepsilon\right)$$

$$\hat{\phi}_k = -\int_0^{x_n} \hat{g}_k(x_{k+1}, \dots, x_{n-1}, \varepsilon)\tilde{\phi}_k(x_{k+1}, \dots, x_{n-1}, \varepsilon)d\varepsilon$$

starting from k=n-1 down to k=1 to bring  $\Sigma_{\rm FFnice}$  into a control-normalized form  $\bar{\Sigma}_{\rm FFnice}: \dot{z}=\bar{f}(z)+\bar{g}(z)u$ 

$$\begin{cases} \bar{f}_j(z) = z_j \tilde{f}_j(z_{j+1}, \dots, z_n) + \hat{f}_j(z_{j+1}, \dots, z_n), & 1 \le j < n \\ \bar{f}_n(z) = 0, & \bar{g}(z) = (0, \dots, 0, 1)^\top \in \Re^n. \end{cases}$$

Ignoring  $\dot{z}_n=u$  (the only component that depends on u),  $\bar{\Sigma}_{\rm FFnice}$  appears as a system in  $\Re^{n-1}$  whose control input is  $z_n$ . If the system is not affine in  $z_n$ , then  $\bar{\Sigma}_{\rm FFnice}$  (hence  $\Sigma_{\rm FFnice}$ ) is not linearizable. Otherwise, the same operation is repeated for  $\bar{\Sigma}_{\rm FFnice}$ , then for its transforms, so on.

## B. Feedback Linearization

Now we analyze the subclass  $\Sigma_{\rm FF\, nice}$  under the feedback group

$$\Gamma : \begin{cases} z = \varphi(x) \\ u = \alpha(x) + \beta(x)v. \end{cases}$$

Notice that  $\varphi$  cannot take any particular form as (II.1) simply because the feedback destroys the (FFnice)-structure unless  $\alpha(x) = \alpha x_n$  and  $\beta(x) = \beta$ , where  $\alpha \in \Re$ ,  $\beta \in \Re^*$ . Before we proceed, recall the following from [5] and [7] (see also [6]).

Theorem II.1: System  $\Sigma: \dot{x} = f(x) + g(x)u$  (not necessarily  $\Sigma_{\mathrm{FF\,nice}}$ ) is locally equivalent, via a feedback transformation  $\Gamma$ , to a linear controllable system  $\Lambda: \dot{w} = Aw + bv$  if and only if (F1)  $\dim \mathrm{span}\mathcal{D}^{n-1} = n$ ; (F2)  $[\mathcal{D}^k, \mathcal{D}^k] \subset \mathcal{D}^k, 0 \le k < n$ .

Here  $\mathcal{D}^k = \operatorname{span}\{g, ad_f g, \dots, ad_f^k g\}$  and (F2) stands for involutivity conditions that are equivalent to the involutivity of  $\mathcal{D}^{n-2}$  (see e.g. [7]). The main result of this section follows.

Theorem II.2: Assume  $\Sigma_{\rm FFnice}$  is  $\mathcal{F}$ -linearizable. We can bring  $\Sigma_{\rm FFnice}$  into a linear controllable system  $\Lambda: \dot{w} = Aw + bu$  via an explicit feedback transformation  $\Gamma$  whose components are obtained by composing, differentiating, inverting, and integrating the components

of  $\Sigma_{\rm FF\, nice}$ . Moreover, the algorithm giving  $\Gamma$  involves a maximum of n(n+3)/2 steps.

The proof is constructive and allows to compute, explicitly, a linearizing change of coordinates and feedback without solving the corresponding PDEs. It appears in the proof that the coordinates changes are globally defined though the inverse of the feedback is only locally guaranteed. Using this equivalent linear form  $\Lambda$ , it is proved in [14] that Mayer's optimal solution for globally feedback linearizable systems always lies on a constraint arc which allows to characterize and build such optimal solution for single-input systems. For multi-input systems, efficient numerical procedures (like pseudospectral method [4]) can be developed. The main difficulty, however, remains in finding linearizing coordinates which underlines the importance of our results. Before we proceed for the proof, we make the following assumption for simplicity.

Assumption 1: For any continuously differentiable function  $w_k = \theta(z_1,\ldots,z_k)$  such that  $\theta(0) = 0$  and  $(\partial\theta/\partial z_k)(0) \neq 0$  we can explicitly find an inverse  $z_k = \mu(z_1,\ldots,z_{k-1},w_k)$ , i.e., a continuously differentiable function  $\mu$ , locally around the origin, such that  $\theta(z_1,\ldots,z_{k-1},\mu(z_1,\ldots,z_{k-1},w_k)) = w_k$ .

Let us make clear that what is assumed is not the existence of the function  $\mu$ , which is guaranteed by the implicit function theorem, but rather the possibility of explicitly computing  $\mu$ . The assumption simplifies the problem but is not necessary; indeed, instead of taking  $\Sigma_{\rm FF\, nice}$  into a linear form  $\dot w = Aw + bu$ , we can always bring it, via explicit coordinates change and feedback, to the feedback form (see [21] for (SFF)-forms)

$$\begin{cases} \dot{w}_j h = w_j \tilde{F}_j(w_{j+1}) + \hat{F}_j(w_{j+1}), \ 1 \le j \le n - 1 \\ \dot{w}_n = v. \end{cases}$$
(II.2)

*Proof of Theorem II.2:* Let  $\bar{\Sigma}_{\mathrm{FFnice}} : \dot{z} = \bar{f}(z) + \bar{g}(z)u$ . Since

$$\bar{f}_{n-1} = z_{n-1}\tilde{f}_{n-1}(z_n) + \hat{f}_{n-1}(z_n) \text{ with } \frac{\partial \hat{f}_{n-1}}{\partial z_n}(0) \neq 0$$

using **Assumption 1** we can apply the change of coordinates

$$w=\psi(z) \stackrel{\Delta}{=} \left\{ \begin{aligned} &w_j=\psi_j(z)=z_j, \ j \neq n-1\\ &w_n=\psi_n(z)=z_{n-1}\tilde{f}_{n-1}(z_n) + \hat{f}_{-n-1}(z_n) \end{aligned} \right.$$

and the feedback  $v=(\partial \bar{f}_{n-1}/\partial z_{n-1})(z)\bar{f}_{n-1}(z_{n-1},z_n)+(\partial \bar{f}_{n-1}/\partial z_n)u$  to transform the system such as  $\bar{f}_{n-1}(z_{n-1},z_n)=z_n$ . Step 1: Involutivity of  $\mathcal{D}^1$  implies  $[\bar{g},ad_{\bar{f}}\bar{g}]=\gamma_1ad_{\bar{f}}\bar{g}+\gamma_0\bar{g}$ , where

 $\gamma_1$  and  $\gamma_0$  are smooth functions. Since  $\bar{g} = \partial/\partial z_n$ ,  $\bar{f}_n(z) = 0$ , and  $\bar{f}_{n-1}(z) = z_n$ , it follows that  $\gamma_0 = \gamma_1 = 0$ . Thus the involutivity of  $\mathcal{D}^1$  reduces to the simple algebraic condition (necessary for  $\mathcal{F}$ -linearization)

$$(\mathcal{F}\mathcal{L}_n) \Longrightarrow \frac{\partial^2 \bar{f}_j}{\partial z_n^2} = 0 \text{ for all } 1 \le j \le n-1$$

that is  $\bar{f}_j(z)=z_j\hat{f}_j(z_{j+1},\ldots,z_n)+\hat{f}_j(z_{j+1},\ldots,z_n)$  are affine in the variable  $z_n$  for all  $1\leq j\leq n$ 

$$\begin{split} \bar{f}_{j}(z) = & z_{j} \left( \tilde{c}_{j}(z_{j+1}, \dots, z_{n-1}) + z_{n} \tilde{b}_{j}(z_{j+1}, \dots, z_{n-1}) \right) \\ &+ \hat{c}_{j}(z_{j+1}, \dots, z_{n-1}) + z_{n} \hat{b}_{j}(z_{j+1}, \dots, z_{n-1}) \\ = & z_{j} \tilde{c}_{j}(z_{j+1}, \dots, z_{n-1}) + \hat{c}_{j}(z_{j+1}, \dots, z_{n-1}) \\ &+ z_{n} \left( z_{j} \tilde{b}_{j}(z_{j+1}, \dots, z_{n-1}) + \hat{b}_{j}(z_{j+1}, \dots, z_{n-1}) \right). \end{split}$$

If  $(\mathcal{F} \mathcal{L}_n)$  fails the algorithm ends: the system is not linearizable. If it holds, then we annihilate all terms containing  $z_n$  in all components (except  $\bar{f}_{n-1}(z_n) = z_n$ ) using n-2 substeps.

General Substep: Assume for some  $1 \le i \le n-2$ , that  $\bar{\Sigma}_{\mathrm{FFnice}}$  has been transformed, by coordinates changes and feedback to

$$\bar{f}_{j}(z) = \begin{cases} z_{j}\tilde{c}_{j}(z_{j+1}, \dots, z_{n-1}) \\ +\hat{c}_{j}(z_{j+1}, \dots, z_{n-1}) \\ +z_{n}\left(z_{j}\tilde{b}_{j}(z_{j+1}, \dots, z_{n-1}) \\ +\hat{b}_{j}(z_{j+1}, \dots, z_{n-1})\right) & \text{if } 1 \leq j \leq i, \\ z_{j}\tilde{c}_{j}(z_{j+1}, \dots, z_{n-1}) \\ +\hat{c}_{j}(z_{j+1}, \dots, z_{n-1}) & \text{if } i+1 \leq j \leq n. \end{cases}$$

It is straightforward that  $w = \psi(z)$  whose components are

$$\begin{cases} w_j = z_j, & j \neq i \\ w_i = z_i \tilde{\psi}_i(z_{i+1}, \dots, z_{n-1}) + \hat{\psi}_i(z_{i+1}, \dots, z_{n-1}) \end{cases}$$

where  $\tilde{\psi}_i(\cdot) = \exp(-\int_0^{z_{n-1}} \tilde{b}_i(z_{i+1}, \dots, z_{n-2}, \varepsilon) d\varepsilon)$  and

$$\hat{\psi}_i(\cdot) = -\int_0^{z_{n-1}} \hat{b}_i(z_{i+1}, \dots, z_{n-2}, \varepsilon) \tilde{\psi}_i(z_{i+1}, \dots, z_{n-2}, \varepsilon) d\varepsilon$$

cancels  $z_n(z_i\tilde{b}_i(z_{i+1},\ldots,z_{n-1})+\hat{b}_i(z_{i+1},\ldots,z_{n-1}))$  in the component  $\bar{f}_i(z)$  still preserving the (FFnice)-form. We transform  $\Sigma_{\rm FFnice}$  via  $\psi=\psi^{n-2}\circ\cdots\circ\psi^1$ , with  $\psi^i$  as above, into

$$\bar{\Sigma}_{\mathrm{FFnice}} : \begin{cases} \bar{f}_{j}(z) = z_{j} \tilde{c}_{j}(z_{j+1}, \dots, z_{n-1}) + \hat{c}_{j}(z_{j+1}, \dots, z_{n-1}) \\ \bar{f}_{n-1}(z) = z_{n}, \bar{f}_{n}(z) = 0, \bar{g}(z) = (0, \dots, 0, 1)^{\top}. \end{cases}$$

Remark that at each substep the inverse of the diffeomorphism is easily computable. Indeed, for the general substep the inverse  $z=\psi^{-1}(w)$  is such that  $z_i=w_i$  for  $j\neq i$  and

$$\begin{split} z_i &= \left[ w_i - \hat{\psi}_i(w_{i+1}, \dots, w_{n-1}) \right] \\ &\times \exp \int\limits_0^{w_{n-1}} \tilde{b}_i(w_{i+1}, \dots, w_{n-2}, \varepsilon) \mathrm{d}\varepsilon. \end{split}$$

Since  $\bar{f}_{n-2}(z) = z_{n-2}\tilde{c}_{n-2}(z_{n-1}) + \hat{c}_{n-2}(z_{n-1})$  with  $(\partial \hat{c}_{n-2}/\partial z_{n-1})(0) \neq 0$ , we can use the assumption to explicitly find the inverse of  $w_{n-1} = z_{n-2}\tilde{c}_{n-2}(z_{n-1}) + \hat{c}_{n-2}(z_{n-1})$ .

Then apply the change of coordinates and feedback

$$\begin{cases} w_j = z_j, j = 1, \dots, n-2, & w_n = \dot{w}_{n-1} \\ w_{n-1} = z_{n-2} \tilde{c}_{n-2} (z_{n-1}) + \hat{c}_{n-2} (z_{n-1}), & v = \dot{w}_n \end{cases}$$

to normalize  $\bar{f}_{n-2} = z_{n-1}$ . This last substep can be omitted in case the system will be brought to the feedback form (II.2).

General Step: Define the projection  $\pi: \Re^n \to \Re^{n-1}$  as  $\pi(z_1,\ldots,z_n)=(z_1,\ldots,z_{n-1})^{\top}$ . The projection  $\pi(\bar{\Sigma}_{\mathrm{FFnice}})$  is a (FFnice)-system in  $\Re^{n-1}$  with control input  $v=z_n$ . The necessary condition for linearization becomes

$$(\mathcal{F}\mathcal{L}_{n-1}) \Longrightarrow \frac{\partial^2 \bar{f}_j}{\partial z_{n-1}^2} \equiv 0, \quad \text{for all } 1 \leq j \leq n-2.$$

We repeat the same procedure as in  $Step\ 1$  to construct coordinates change that annihilates all terms containing the variable  $z_{n-1}$ . The diffeomorphism obtained is thus extended in  $\Re^n$  by adding the nth component as identity. Then a feedback is applied as above to normalize the 2nd last component (in this case  $\bar{f}_{n-3}(z)=z_{n-2}$ ). The procedure will be repeated (n-2) times as long as the corresponding  $(\mathcal{F}\pounds_n)$  conditions are satisfied for the corresponding system. The diffeomorphisms  $\phi$  and  $\psi$  taking  $\Sigma_{\mathrm{FFnice}}$  into a control-normalized  $\bar{\Sigma}_{\mathrm{FFnice}}$  and  $\bar{\Sigma}_{\mathrm{FFnice}}$  into the Brunovský canonical form are obtained by integrations, derivations, compositions of the components of  $\Sigma_{\mathrm{FFnice}}$ , and

 $\bar{\Sigma}_{\mathrm{FF\, nice}}$ , respectively. The feedback is obtained in general by inverting a nonlinear function (**Assumption 1**) but can be circumvented if we transform the system into (II.2). One can easily check that there is a maximum of  $n+n+(n-1)+\cdots+1=n(n+3)/2$  substeps, a difference of n substeps with the  $\mathcal{S}$ -linearization due to the use of feedback.

Example II.3: Let us consider the system in (FFnice)-form

$$\Sigma_{\mathrm{FF\,nice}} : \left\{ \begin{array}{ll} \dot{x}_1 = \sin\frac{x_2}{1+x_4^2} + x_4 \sin x_3 + \frac{x_2}{1+x_4^2} u, & \dot{x}_3 = \sin x_4 \\ \dot{x}_2 = \left(1 + x_4^2\right) \sin x_3 + \frac{2x_2x_4}{1+x_4^2} u, & \dot{x}_4 = u \end{array} \right. .$$

We rectify  $g(x) = ((x_2/(1+x_4^2)), (2x_2x_4/(1+x_4^2)), 0, 1)^{\top}$  and put  $\Sigma_{\rm FF\, nice}$  in  $\bar{\Sigma}_{\rm FF\, nice}$ . Since  $g_2(x) = (2x_2x_4/(1+x_4^2)) = x_2\tilde{g}_2(x_3,x_4) + \hat{g}_2(x_3,x_4)$  with  $\tilde{g}_2(x_3,x_4) = 2x_4/(1+x_4^2)$  and  $\hat{g}_2(x_3,x_4) = 0$ , a change of coordinates annihilating the component  $g_2$  is

$$\begin{cases} \tilde{x}_1 = x_1, & \tilde{x}_3 = x_3\\ \tilde{x}_2 = x_2 \exp\left(\int_0^{x_4} \tilde{g}_2(x_3, \varepsilon) d\varepsilon\right) = \frac{x_2}{1 + x_4^2}, & \tilde{x}_4 = x_4 \end{cases}$$

with inverse

$$\begin{cases} x_1 = \tilde{x}_1, & x_3 = \tilde{x}_3 \\ x_2 = \tilde{x}_2 (1 + \tilde{x}_4^2), & x_4 = \tilde{x}_4. \end{cases}$$

It transforms the system into

$$\begin{cases} \dot{\tilde{x}}_1 = \sin \tilde{x}_2 + \tilde{x}_4 \sin \tilde{x}_3 + \tilde{x}_2 u, & \dot{\tilde{x}}_3 = \sin \tilde{x}_4 \\ \dot{\tilde{x}}_2 = \sin \tilde{x}_3, & \dot{\tilde{x}}_4 = u. \end{cases}$$

Now  $g(\tilde{x}) = (\tilde{x}_2, 0, 0, 1)^{\top}$  and  $g_1 = \tilde{x}_2 = \tilde{x}_1 \tilde{g}_1(\tilde{x}) + \hat{g}_1(\tilde{x})$  with  $\tilde{g}_1 = 0$  and  $\hat{g}_1 = \tilde{x}_2$ . Thus the change of coordinates

$$\begin{cases} z_1 = \tilde{x}_1 \tilde{\phi}_1(\tilde{x}) + \hat{\phi}_1(\tilde{x}) = \tilde{x}_1 - \tilde{x}_2 \tilde{x}_4 \\ z_j = \tilde{x}_j, & j \neq 1 \end{cases}$$

with  $\tilde{\phi}_1(\tilde{x}) = \exp(-\int_0^{\tilde{x}_4} \tilde{g}_1(\tilde{x}_2, \tilde{x}_3, \varepsilon) d\varepsilon) = 1$  and

$$\hat{\phi}_1(\tilde{x}_2, \tilde{x}_3, \tilde{x}_4) = \int\limits_0^{\tilde{x}_4} \hat{g}_1(\tilde{x}_2, \tilde{x}_3, \varepsilon) \tilde{\phi}_1(\tilde{x}_2, \tilde{x}_3, \varepsilon) d\varepsilon = -\tilde{x}_2 \tilde{x}_4$$

annihilates  $g_1$  and brings  $\Sigma_{\rm FFnice}$  into  $\bar{\Sigma}_{\rm FFnice}$ :

$$\bar{\Sigma}_{\text{FF nice}} : \begin{cases} \dot{z}_1 = \sin z_2, & \dot{z}_3 = \sin z_4 \\ \dot{z}_2 = \sin z_3, & \dot{z}_4 = u. \end{cases}$$

The change of coordinates  $w = \psi(z)$ 

$$\begin{cases} w_1 = z_1, & w_3 = \cos z_2 \sin z_3 \\ w_2 = \sin z_2, & w_4 = -\sin z_2 \sin^2 z_3 + \cos z_2 \cos z_3 \sin z_4 \end{cases}$$

and feedback  $v=(\partial w_4/\partial z_2)\sin z_3+(\partial w_4/\partial z_3)\sin z_4+(\partial w_4/\partial z_4)u$  linearizes the system:  $\dot{w}_1=w_2,\,\dot{w}_2=w_3,\,\dot{w}_3=w_4,\,\dot{w}_4=v$ . The feedback law  $(p(\lambda)=\lambda^4+k_1\lambda^3+k_2\lambda^2+k_3\lambda+k_4)$  Hurwitz)

$$u = -\frac{\sin z_3 \frac{\partial \psi_4}{\partial z_2} + \sin z_4 \frac{\partial \psi_4}{\partial z_3} + k_1 \psi_1(z) + \dots + k_4 \psi_4(z)}{\cos z_2 \cos_3 \cos z_4}$$

re-expressed in original coordinates, locally asymptotically stabilizes the system on  $(-\epsilon, \epsilon)^n$  for  $0 < \epsilon < \pi/2$ .

Example II.4: Consider a simplified model of a VTOL with dynamics [15] (see Fig. 1.)<sup>1</sup>




Fig. 1. Forces acting on the aircraft.

$$\begin{cases} \dot{x}_1 = x_2, & \dot{x}_2 = -\sin(\theta_1) \frac{T}{M} + \cos(\theta_1) \frac{2\sin\alpha}{M} F \\ \dot{y}_1 = y_2, & \dot{y}_2 = -\cos(\theta_1) \frac{T}{M} + \sin(\theta_1) \frac{2\sin\alpha}{M} F - \mathfrak{g} \\ \dot{\theta}_1 = \theta_2, & \dot{\theta}_2 = \frac{2l}{T} \cos\alpha F \end{cases}$$
 (II.3)

where M,J,l and  $\mathfrak g$  denote the mass, moment of inertia, distance between wingtips and gravitational acceleration. The control inputs are the thrust T, and the rolling moment due to the torque F, whose direction forms a fixed angle  $\alpha$  with the horizontal body axis. The position of center mass and the roll angle with respect to the horizon are  $(x_1,y_1)$ , and  $\theta_1$  while  $(x_2,y_2)$  and  $\theta_2$  stand for their respective velocities. Thus the system is a two-input control system in (SFF)-form. Let fix  $T=-M(\mathfrak g-y_2)\cos\theta_1$  so as to compensate the force due to acceleration (sign minus denotes opposite direction to that force) and normalize M,J, and l to 1. Taking u=F as control input, and  $x_3=y_1,x_4=y_2,x_5=\theta_1,x_6=\theta_2/2\cos\alpha$ , the system rewrites  $\Sigma:\dot{x}=f(x)+g(x)u,x\in\Re^6,u\in\Re$  with

$$f(x) = (x_2, (\mathfrak{g} - x_4) \sin x_5 \cos x_5, x_4, -\mathfrak{g} \sin^2 x_5 - x_4 \cos^2 x_5, 2 \cos \alpha x_6, 0)^{\top} g(x) = (0, 2 \sin \alpha \cos x_5, 0, 2 \sin \alpha \sin x_5, 0, 1)^{\top}.$$

This system is in (FFnice)-form. Since  $g_1, g_3, g_5$  are zero and  $g_6 = 1$ , only two substeps are required to rectify g.

To cancel  $g_4(x)=2\sin\alpha\sin x_5$ , observe that  $g_4(x)=x_4\tilde{g}_4(x_5,x_6)+\hat{g}_4(x_5,x_6)$  with  $\tilde{g}_4=0$  and  $\hat{g}_4=2\sin\alpha\sin x_5$ . Thus  $\phi_4(x)=x_4\hat{\phi}_4(x)+\hat{\phi}_4(x)$  with  $\hat{\phi}_4(x)=1$ ,  $\hat{\phi}_4(x)=-\int_0^{x_6}2\sin\alpha\sin x_5\mathrm{d}\varepsilon=-2\sin\alpha(\sin x_5)x_6$ . It follows that the change of coordinates (and its inverse):

$$z = \phi(x) \triangleq \begin{cases} z_j = x_j, & j \neq 4, \\ z_4 = x_4 - 2\sin\alpha(\sin x_5)x_6 \end{cases}$$
$$x = \psi(z) \triangleq \begin{cases} x_j = z_j, & j \neq 4, \\ x_4 = z_4 + 2\sin\alpha(\sin z_5)z_6 \end{cases}$$

transform the system  $\Sigma_{\rm FFnice}$  into (keep same notation)

$$\begin{cases} x_1 = x_2 \\ \dot{x}_2 = (\mathfrak{g} - x_4 - 2\sin\alpha(\sin x_5)x_6)\sin x_5\cos x_5 \\ +2\sin\alpha\cos x_5 u \\ \dot{x}_3 = x_4 + 2\sin\alpha(\sin x_5)x_6 \\ \dot{x}_4 = -\mathfrak{g}\sin^2 x_5 - (x_4 + 2\sin\alpha(\sin x_5)x_6)\cos^2 x_5 \\ -2\sin\alpha(\cos x_5)x_6^2 \\ \dot{x}_5 = (2\cos\alpha)x_6 \\ \dot{x}_6 = u \end{cases}$$

<sup>&</sup>lt;sup>1</sup>A special thank you to Linda G. for her invaluable assistance.

with control vector field  $g(x) = (0, 2 \sin \alpha \cos x_5, 0, 0, 0, 1)^{\top}$ . To annihilate  $g_2(x)$ , we calculate  $\phi_2(x) = x_2 \tilde{\phi}_2(x) + \hat{\phi}_2(x)$ . Thus the change of coordinates (and its inverse)

$$z = \phi(x) \triangleq \begin{cases} z_j = x_j, & j \neq 2, \\ z_2 = x_2 - 2\sin\alpha(\cos x_5)x_6 \end{cases}$$
$$x = \psi(z) \triangleq \begin{cases} x_j = z_j, & j \neq 2 \\ x_2 = z_2 + 2\sin\alpha(\cos z_5)z_6 \end{cases}$$

transform the latter system into  $\bar{\Sigma}_{\mathrm{FFnice}}$ :  $\dot{z} = \bar{f}(z) + \bar{g}(z)u$ 

$$\begin{cases} \dot{z}_1 = z_2 + 2\sin\alpha(\cos z_5)z_6 \\ \dot{z}_2 = (\mathfrak{g} - z_4 - 2\sin\alpha(\sin z_5)z_6)\sin z_5\cos z_5 \\ + 2\sin\alpha(\sin z_5)z_6^2 \\ \dot{z}_3 = z_4 + 2\sin\alpha(\sin z_5)z_6 \\ \dot{z}_4 = -\mathfrak{g}\sin^2 z_5 - (z_4 + 2\sin\alpha(\sin z_5)z_6)\cos^2 z_5 \\ - 2\sin\alpha(\cos z_5)z_6^2 \\ \dot{z}_5 = (2\cos\alpha)z_6 \\ \dot{z}_6 = u. \end{cases}$$

Since  $\partial^2 \bar{f}_1/\partial z_6^2 = 0 \cdot (\partial \bar{f}_1/\partial z_6)$  while  $\partial^2 \bar{f}_2/\partial z_6^2 \neq 0 \cdot (\partial \bar{f}_2/\partial z_6)$ , condition  $(\mathcal{F}\mathcal{L}_6) \Longrightarrow (\partial^2 \bar{f}_j/\partial z_6^2) = \gamma_1(z)(\partial \bar{f}_j/\partial z_6), 1 \leq j \leq 5$  fails because  $\gamma_1(z)$  is not unique. Thus, the system is not  $\mathcal{F}$ -linearizable.

## III. LINEARIZABLE SYSTEMS OF TYPE II

Consider Type II (SFF)-systems described in [10] by

$$\begin{cases} \dot{x}_j = x_{j+1} + g_j(x_{j+1}, \dots, x_n)u, \ 1 \le j < n \\ \dot{x}_n = u \end{cases}$$
 (III.1)

where  $g_1, \ldots, g_{n-1}$  are smooth functions,  $g_i(0) = 0$ . Type II have a linear drift f(x) = Ax while Type I take the form

$$\begin{cases} \dot{x}_1 = x_2 + \sum_{j=2}^{n-1} \pi_i(x_i) x_{i+1} + \pi_n(x_n) u \\ \dot{x}_j = x_{j+1}, \quad j = 2, \dots, n-1 \\ \dot{x}_n = u \end{cases}$$

and were introduced in [9], [10] (see also [17], [20] beyond that class), where it is showed that a linearizing coordinates is

$$w = \varphi(x) \triangleq \begin{cases} w_1 = x_1 - \sum_{i=2}^n \int_0^{x_i} \pi_i(\varepsilon) d\varepsilon \\ w_j = x_j, \quad j = 2, \dots, n. \end{cases}$$

For *Type II* systems, Krstic [10] defined recursively the functions  $\mu_n(x_n), \ldots, \mu_2(x_n)$  for  $i = n, \ldots, 2$  as

$$\mu_{i} = \frac{1}{x_{n}} \int_{0}^{x_{n}} (g_{i-1}(0, \dots, 0, \varepsilon))$$
$$- \sum_{i=i+1}^{n} \mu_{j}(\varepsilon) g_{i+n-j}(0, \dots, 0, \varepsilon) d\varepsilon. \quad \text{(III.2)}$$

Next, he defined  $\gamma_k(x)_n$  for  $k=1,\ldots,n-2$  as

$$\gamma_k = \sum_{l=1}^{k-1} \gamma_l(x_n) \mu_{l+n+1-k}(x_n) + \mu'_{n+1-k}(x_n).$$
 (III.3)

He then obtained the following result.

Theorem III.1 (Krstic [10]): If

$$g_i(x_{i+1}, \dots, x_n) = \sum_{j=i+1}^{n-1} \gamma_{j-i}(x_n) x_j + g_i(0, \dots, 0, x_n) \quad \text{(III.4)}$$

 $\forall x, 1 \leq i \leq n-2$ , then the diffeomorphic transformation

$$\begin{cases} w_i = x_i - \sum_{j=i+1}^{n-1} \mu_{i+n+1-j}(x_n) x_j, \ 1 \le i \le n-1 \\ w_n = x_n \end{cases}$$
 (III.5)

converts the *(SFF)*-system (III.1) into the chain of integrators  $\dot{w}_1 = w_2, \ldots, \dot{w}_{n-1} = w_n, \dot{w}_n = u$ . Thus  $u = -\sum_{i=1}^n C_n^{i-1} w_i$  globally asymptotically stabilizes the origin of (III.1).

Observe that (III.4) is in the form

$$g_i(x_{i+1},\ldots,x_n) = \sum_{j=i+1}^n \beta_{i,j}(x_n)x_j, \quad 1 \le i \le n-1$$
 (III.6)

with  $\beta_{i,j}(x_n) = \gamma_{j-i}(x_n)$  and  $\beta_{i,n}(x_n) = g_i(0,\ldots,0,x_n)$ . We say that (III.1) is *quasilinear* if (III.6) holds for some functions  $\beta_{i,j}(x_n)$ . Clearly, (III.1) given by (III.4) is quasilinear and linearizable provided the coefficients  $\gamma_k$  satisfy (III.3) with  $\mu_k$  given by (III.2). *Does any linearizable quasilinear system satisfy* (III.2)-(III.3)-(III.4)? We will show that the answer is yes. Notice that (III.1)–(III.6) can be put in the compact form

$$\dot{x} = Ax + g(x)u = Ax + bu + B(x_n)xu \tag{III.7}$$

with (A,b) the Brunovský pair, and  $B=(\beta_{i,j}(x_n))_{1\leq i< j\leq n}$  a upper triangular nilpotent matrix (u.t.n.m) whose entries are smooth functions of the variable  $x_n$ . The main result of this section is the characterization of the linearizability of (III.7).

*Theorem III.2:* Let (III.1)–(III.6) be quasilinear or in compact form (III.7). The three conditions below are equivalent.

- (i) System (III.7) is linearizable by change of coordinates.
- (ii) There exists an invertible (u.t.m)  $M = (\alpha_{i,j}(x_n))_{1 \le i \le j \le n}$  s. t.

$$\begin{cases} AM = MA, \\ Mb + (MB + M')x = b & \text{for all } x \in \Re^n. \end{cases}$$
 (III.8)

(iii) System (III.7) is in the form (III.4) with  $\gamma_k$  given by (III.3) and  $\mu_k$  given by (III.2).

Theorem III.2 establishes the fact that the linearizability conditions (III.6) with (III.3), (III.4) obtained by Krstic are necessary and sufficient for the quasilinear systems (recall not all *Type II* systems are linearizable). As a consequence we deduce the following algorithm whose importance is two fold: (a) it allows to test whether a quasilinear system is linearizable or not, and (b) when linearizable, it gives a linearizing change of coordinates. Let us recall that a matrix  $M = (\alpha_{i,j}(x_n))_{1 \le i \le j \le n}$  is said to be in *Toeplitz form* if  $\forall 1 \le i \le j \le n$ 

$$\alpha_{i,j}(x_n) = \alpha_{i+1,j+1}(x_n) = \dots = \alpha_{i+n-j,n}(x_n).$$
 (III.9)

Linearization Procedure: Consider the (SFF)-system (III.7).

- Step 1) Take  $\hat{B}$  as the matrix B with the last row and last column deleted. If  $\hat{B}$  is not a (u.t.n.m) in *Toeplitz form*, then STOP, the system is not linearizable.
- Step 2) If  $\hat{B}$  is a (*u.t.n.m*) in *Toeplitz form*, solve  $\hat{M}\hat{B} + \hat{M}' = 0$  to get  $\hat{M}$ . Then compute the function  $\alpha_{1,n}(x_n)$  via

$$\alpha_{1,n}(x_n) = -\frac{1}{x_n} \sum_{k=1}^{n-1} \int_{0}^{x_n} \alpha_{1,k}(\varepsilon) \beta_{k,n}(\varepsilon) \varepsilon d\varepsilon.$$
 (III.10)

Since M should be *Toeplitz*, the obtention of  $\hat{M}$  and  $\alpha_{1,n}$  gives M by adding to  $\hat{M}$  the last column and row accordingly.

Step 3) If  $B_n$  (resp.  $M_n$ ) is the last column of B (resp. M), check if  $M_n + x_n(MB_n + M'_n) = b$ . If no, the system is not linearizable and if yes, it is by  $w = M(x_n)x$ .

*Proof of Theorem III.2:* We will show (iii)  $\Rightarrow$  (i)  $\Rightarrow$  (ii)  $\Rightarrow$  (iii).

- $(iii) \Rightarrow (i)$  is direct and can be deduced from Theorem III.1.
- (i)  $\Rightarrow$  (ii) We proved in [20] that (III.1) in  $\Re^3$ , is linearizable iff  $g_1 = x_2\gamma_1(x_3) + \theta_1(x_3)$ , where  $\gamma_1(x_3) = (d/dx_3)((1/x_3)\int_0^{x_3}g_2(\varepsilon)\mathrm{d}\varepsilon)$ . The (u.t.m)  $M = (\alpha_{i,j}(x_3))_{1 < i < j < 3}$

$$\alpha_{i,i}=1,\quad 1\leq i\leq 3,\quad \alpha_{1,2}(x_3)=-\frac{1}{x_3}\int\limits_{-x_3}^{x_3}g_2(\varepsilon)\mathrm{d}\varepsilon$$

$$\alpha_{1,3}(x_3) = -\frac{1}{x_3} \left( \int_0^{x_3} \gamma_1(\varepsilon) d\varepsilon - \int_0^{x_3} \alpha_{1,2}(\varepsilon) g_2(\varepsilon) d\varepsilon \right)$$

satisfies (III.8) and defines  $w=M(x_3)x$  that linearizes the system. Assume the implication true for systems in  $\Re^{n-1}$ . Let (III.1) be an n-dimensional system linearizable by  $w=\varphi(x)=(\varphi_1(x_1,\ldots,x_n),\varphi_2(x_2,\ldots,x_n),\ldots,\varphi_n(x_n))^{\top}$ . Set  $\rho(x_1,\ldots,x_n)=(x_2,\ldots,x_n)^{\top}$ . The projection  $\rho(\Sigma)$  is linearizable by  $\rho(\varphi(x))=(\varphi_2(x_2,\ldots,x_n),\ldots,\varphi_n(x_n))^{\top}$ . By induction  $\varphi_i(x)=x_i+\sum_{j=i+1}^n\alpha_{i,j}(x_n)x_j$  for  $i\geq 2$  with  $\alpha_{i,j}=\alpha_{i-1,j-1}$ . Since  $w=\varphi(x)$  linearizes the system,  $w=(\partial\varphi/\partial x)Ax+(\partial\varphi/\partial x)bu+(\partial\varphi/\partial x)B(x_n)xu=A\varphi(x)+bu$ . Thus  $A\varphi(x)=L_{Ax}\varphi(x)$  which implies  $\varphi_2(x)=L_{Ax}\varphi(x)+bu$ . Also  $\varphi_2(x)=x_2+\sum_{j=3}^n\alpha_{2,j}(x_n)x_j=L_{Ax}(x_1+\sum_{j=2}^{n-1}\alpha_{1,j}(x_n)x_j)$ . We then deduce that  $\varphi_1(x)=x_1+\sum_{j=2}^{n-1}\alpha_{1,j}(x_n)x_j+\theta(x_n)$ . The change of coordinates  $w=\varphi(x)$  is in the form  $w=M(x_n)x$ , where  $M(x_n)$  satisfies (III.8) necessarily.

• (ii)  $\Rightarrow$  (iii) Consider the system (III.7) and assume that  $M=(\alpha_{i,j}(x_n))_{1\leq i\leq j\leq n}$  exists and satisfies (III.8). Define  $\mu_k$  and  $\gamma_k$  such that for  $1\leq i< j\leq n-1$  we have  $\beta_{i,j}(x_n)=\gamma_{j-i}(x_n)$  and for  $1\leq i< j\leq n$  we have  $\alpha_{i,j}(x_n)=-\mu_{i+1+n-j}(x_n)$ . This is possible provided that (III.9) is satisfied. That's the only point we need to clarify because Mb+(MB+M')x=b for all  $x\in\Re^n$  is already equivalent to (III.2)-(III.3)-(III.4). Condition (III.9) is satisfied since AM=MA. Let  $\hat{M}$  (resp.  $\hat{B}$ ) denote the matrice M (resp. B) with the last row and last column deleted. Mb+(MB+M')x=b for all  $x\in\Re^n$  implies that  $\hat{M}\hat{B}+\hat{M}'=0$ .  $\hat{M}$  being in Toeplitz form (hence is  $\hat{M}'$ ) and invertible, thus  $\hat{B}=\hat{M}^{-1}\hat{M}'$  is also in Toeplitz form.

Example III.3: Reconsider Example II.3 and let a = 0, that is

$$\begin{cases} \dot{x}_1 = x_2 + \left(\frac{1}{2}x_2 - \frac{1}{12}x_3x_4\right)u, & \dot{x}_3 = x_4 + x_4u\\ \dot{x}_2 = x_3 + \frac{1}{2}x_3u, & \dot{x}_4 = u. \end{cases}$$

This is a quasilinear (SFF)-system  $\dot{x} = Ax + bu + B(x_4)xu$  in  $\Re^4$ , where  $B = (\beta_{i,j})$  is a (*u.t.n.m*) with  $\beta_{1,4} = \beta_{2,4} = 0$ 

$$\beta_{1,2}(x_4) = \beta_{2,3}(x_4) = \frac{1}{2}, \quad \beta_{1,3}(x_4) = -\frac{1}{2}, \quad \beta_{3,4}(x_4) = 1.$$

We look for an invertible (*u.t.m*)  $M=(\alpha_{i,j})$  in *Toeplitz form*, i. e.,  $\alpha_{i,i}=1,1\leq i\leq 4; \alpha_{1,2}=\alpha_{2,3}=\alpha_{3,4}$  and  $\alpha_{1,3}=\alpha_{2,4}$  such that  $\hat{M}\hat{B}+\hat{M}'=0$ . We deduce the system of ordinary differential equations (ODEs):  $\alpha'_{1,3}(x_4)-(1/12)x_4+(1/2)\alpha_{1,2}(x_4)=0, \alpha'_{1,2}(x_4)+(1/2)=0$  which yields  $\alpha_{1,2}=-(1/2)x_4$  and  $\alpha_{1,3}=(1/6)x_4^2$ . Integrating (III.10) for  $\beta_{1,4}=\beta_{2,4}=0, \beta_{3,4}=1$  gives  $\alpha_{1,4}(x_4)=1$ 

 $-(1/24)x_4^3$ . Hence the change of coordinates  $w=M(x_4)x$  defined by

$$\begin{cases} w_1 = x_1 - \frac{1}{2}x_2x_4 + \frac{1}{6}x_3x_4^2 - \frac{1}{24}x_4^4, & w_3 = x_3 - \frac{1}{2}x_4^2 \\ w_2 = x_2 - \frac{1}{2}x_3x_4 + \frac{1}{6}x_4^3, & w_4 = x_4 \end{cases}$$

linearizes the system (compare with Example II.3 when a=0).

#### IV. CONCLUSION

In this technical note we considered a subclass of single input control systems in feedforward form, namely (FFnice), for which we gave a feedback linearizing algorithm. The importance of the algorithm is two fold: (a) it replaces the solving of the PDEs by simple algebraic operations involving differentiating, integrating, and composing functions only; (b) it does not require an a priori checking of the feedback linearization conditions of Theorem II.1 (which is usually very hard). Indeed, at each step those conditions are replaced with the fact that the second derivative of a certain vector field is proportional to its first derivative with respect to the same variable. Moreover, the algorithm allows to compute a stabilizing feedback controller for the original system. The drawback of the linearization technique in general is that some global properties can be lost during the operation. For feedforward systems however, the transformations we obtained are globally defined though their inverses might not be. A generalization of our results to multi-input control systems is under investigation for (SFF) and (FFnice) systems. The VTOL example, which is a 2-input control system, falls in that class of (FF)-systems. As mentioned earlier, when the system is not (FFnice), that is, at least one component is nonlinear with respect to the corresponding variable, then the PDEs cannot be separated into ODEs. Extending those results outside the class of (FF)-systems requires a different approach and is already challenging for single-input systems. We are currently working in that direction with promising results and we are expecting that the new algorithms will cover all linearizable systems.

## REFERENCES

- [1] J. Alvarez-Gallegos, "Nonlinear regulation of a Lorenz system by feedback linearization techniques," *Dyn. & Control*, pp. 277–298, 1994.
- [2] A. Astolfi and G. Kaliora, "A geometric characterization of feed-forward forms," *IEEE Trans. Autom. Control*, vol. 50, no. 7, pp. 1016–1021, Jul. 2005.
- [3] R. W. Brockett, "Feedback invariants for nonlinear systems," in *Proc. Int. Congress Math.*, 1978, pp. 1357–1368.
- [4] Q. Gong, W. Kang, and I. M. Ross, "A pseudospectral method for the optimial control of constrained feedback linearizable systems," *IEEE Trans. Autom. Control*, vol. 51, no. 7, pp. 1115–1129, Jul. 2006.
- [5] L. R. Hunt and R. Su, "Linear equivalents of nonlinear time varying systems," in *Proc. Math. Theory Networks Syst.*, Santa Monica, CA, 1981, pp. 119–123.
- [6] A. Isidori, Nonlinear Control Systems, 2nd ed. New York: Springer, 1989.
- [7] B. Jakubczyk and W. Respondek, "On linearization of control systems," B. Acad. Pol. Sci. Séries Math., vol. 28, pp. 517–522, 1980.
- [8] A. J. Krener, "On the equivalence of control systems & linearization of nonlinear systems," Siam J. Control, vol. 11, pp. 670–676, 1973.
- [9] M. Krstic, "Feedforward systems linearizable by coordinate change," in *Proc. Amer. Control Conf.*, Boston, MA, 2004, pp. 4348–4353.
- [10] M. Krstic, "Feedback linearizability and explicit integrator forwarding controllers for classes of feedforward systems," *IEEE Trans. Autom. Control*, vol. 49, no. 10, pp. 1668–1682, Oct. 2004.
- [11] C. Liqun and L. Yanzhu, "Control of the Lorenz chaos by the exact linearization," *Appl. Math. Mech.*, vol. 19, pp. 67–73, 1998.
- [12] P. Mullhaupt, "Quotient submanifolds for static feedback linearization," Syst. Control Lett., vol. 55, pp. 549–557, 2006.
- [13] W. Respondek and I. A. Tall, "Smooth and analytic normal and canonical forms for strict feedforward systems," in *Proc. 44th IEEE Conf. Decision Control*, Seville, Spain, 2005, pp. 4213–4218.
- [14] M. Schlemmer and S. K. Agrawal, "Globally feedback linearizable time-invariant systems: Optimal solution for Mayer's problem," J. Dyn. Syst., Meas. Control, vol. 122, no. 2, pp. 343–347, 2000.

- [15] A. Serrani, A. Isidori, C. I. Byrnes, and L. Marconi, "Recent advances in output regulation of nonlinear systems," in *Nonlinear Control in the Year 2000*, A. Isidori, F. Lamnabhi-Lagarrigue, and W. Respondek, Eds. New York: Springer, 2000, vol. 259, pp. 409–419, 2.
- [16] I. A. Tall and W. Respondek, "Feedback equivalence to feedforward form for nonlinear single-input systems," in *Dyn., Bifur. Control*, F. Colonius and L. Grüne, Eds. London, U.K.: Springer, 2002, vol. 273, pp. 269–286.
- [17] I. A. Tall, "Linearizable feedforward systems: A special class," in Proc. 17th IEEE Int. Conf. Control Appl., San Antonio, TX, 2008, pp. 1201–1206.
- [18] I. A. Tall, "State linearization of control systems: An explicit algorithm," in *Proc. Joint 48th IEEE Conf. Decision Control/28th Chinese Control Conf.*, Shanghai, China, Dec. 2009, pp. 7448–7453.
- [19] I. A. Tall, "Explicit feedback linearization of control systems," in *Proc. Joint 48th IEEE Conf. Decision Control/28th Chinese Control Conf.*, Shanghai, China, Dec. 2009, pp. 7454–7459.
- [20] I. A. Tall and W. Respondek, "On linearizability of strict feedforward systems," in *Proc. Amer. Control Conf.*, 2008, pp. 1929–1934.
- [21] I. A. Tall and W. Respondek, "Feedback linearizable strict feedforward systems," in *Proc. 47th IEEE Conf. Decision Control*, Cancün, Mexico, 2008, pp. 2499–2504.
- [22] A. Teel, Feedback Stabilization: Nonlinear Solutions to Inherently Nonlinear Problems Memorandum UCB/ERL M92/65.
- [23] A. Teel, "A nonlinear small gain theorem for the analysis of control systems with saturation," *IEEE Trans. Autom. Control*, vol. 41, no. 9, pp. 1256–1270, Sep. 1996.

## A Pontryagin's Maximum Principle for Non-Zero Sum Differential Games of BSDEs with Applications

Guangchen Wang and Zhiyong Yu

Abstract—This technical note is concerned with a maximum principle for a new class of non-zero sum stochastic differential games. The most distinguishing feature, compared with the existing literature, is that the game systems are described by backward stochastic differential equations (BSDEs). This kind of games are motivated by some interesting phenomena arising from financial markets and can be used to characterize the players with different levels of utilities. We establish a necessary condition and a sufficient condition in the form of maximum principle for open-loop equilibrium point of the foregoing games respectively. To explain the theoretical results, we use them to study a financial problem.

Index Terms—Backward stochastic differential equation (BSDE), nonzero sum stochastic differential game, open-loop equilibrium point, Pontryagin's maximum principle, portfolio choice.

### I. INTRODUCTION

#### A. Basic Notations and Problem Formulation

THROUGHOUT this technical note, we denote by  $\mathbb{R}^k$  the k-dimensional Euclidean space,  $\mathbb{R}^{k \times l}$  the collection of  $k \times l$  matrices. For a given Euclidean space, we denote by  $\langle \cdot, \cdot \rangle$  (respectively,  $|\cdot|$ ) the scalar product (respectively, norm). The superscript  $\tau$  denotes the transpose of vectors or matrices. Let  $(\Omega, \mathcal{F}, (\mathcal{F}_t), \mathbb{P})$  be a complete filtered probability space equipped with a natural filtration

$$\mathcal{F}_t = \sigma\{W(s); 0 \le s \le t\}, \quad t \in [0, T]$$

where  $(W(\cdot))$  is an  $\mathbb{R}^m$ -valued standard Brownian motion defined on the space, T>0 is a fixed time horizon, and  $\mathcal{F}=\mathcal{F}_T$ . If  $x:[0,T]\times\Omega\to\mathbb{R}^l$  is an  $\mathcal{F}_t$ -adapted square-integrable process (i.e.,  $\mathbb{E}\int_0^T|x(t)|^2dt<+\infty$ ), then we write  $x\in L^2_{\mathcal{F}}(0,T;\mathbb{R}^l)$ . For simplicity, sometimes we throw away  $\mathbb{R}^l$  when there is no danger of confusion.

In this technical note, we study a class of non-zero sum differential games of BSDEs, which is inspirited by some interesting financial phenomena. For simplicity, we only consider the case of two players, which is similar for n players. Let us now give a detailed formulation of the problem. Consider the following BSDE:

$$\begin{cases} -dy^{v_1,v_2}(t) = f(t,y^{v_1,v_2}(t),z^{v_1,v_2}(t),v_1(t),v_2(t))dt \\ -z^{v_1,v_2}(t)dW(t), \end{cases} \tag{1}$$

$$y^{v_1,v_2}(T) = \xi.$$

Manuscript received April 19, 2009; revised September 09, 2009. First published April 12, 2010; current version published July 08, 2010. This work was supported by the National Natural Science Foundation (10926098), the Natural Science Foundation of Shandong Province (2008BS01024, ZR2009AQ017), the startup foundation of doctoral research program of Shandong Normal University, the Youth Foundation of the School of Mathematical Sciences, Shandong Normal University, the National Basic Research Program of China (973 Program 2007CB814901), the National Natural Science Foundation (10871118), and the Independent Innovation Foundation of Shandong University (2009TS036). Recommended by Associate Editor P. Shi.

- G. Wang is with the School of Mathematical Sciences, Shandong Normal University, Jinan 250014, China (e-mail: wgcmathsdu@sohu.com; wguangchen@mail.sdu.edu.cn).
- Z. Yu is with the School of Economics, Shandong University, Jinan 250100, China. He is also with the Département de Mathématiques, Université d'Évry Val d'Essonne, Évry cedex 91025, France (e-mail: yuzhiyong@sdu.edu.cn).

Digital Object Identifier 10.1109/TAC.2010.2048052